

VC550-6

DIESEL GENERATOR SET / OPEN + SILENT



OPEN SET



SILENT SET

550

kVA

STANDBY POWER

500

kVA

PRIME POWER

60

Hz

FREQUENCY

440/254

V

VOLTAGE

Cummins KTA19-G3

3 phase · 0.8 PF · 1800 rpm

CONFIGURATION COMPARISON

Configuration	Dimensions (L × W × H)	Dry weight	Fuel tank
Open set	3200 × 1390 × 2135 mm	3220 kg	750 L
Silent set	4350 × 1450 × 2327 mm	4620 kg	750 L

Performance, engine, alternator and controller data are common to both configurations.

GENERAL CHARACTERISTICS

VC550-6 · 60 Hz · 3 Phase

RATED PERFORMANCE

Standby Power (kVA)	550
Standby Power (kW)	440
Prime Power (kVA)	500
Prime Power (kW)	400
Power Factor (Cos Phi)	0.8
Diesel Engine	KTA19-G3
Frequency (Hz)	60
Rated Speed (rpm)	1800
Phase	3
Standard Voltage (V)	440/254
Available Voltages (V)	220/127 or 480/277

POWER DEFINITIONS

STANDBY POWER (ESP)

Available for supplying emergency power during a utility interruption. The stated rating follows ISO 8528-1.

PRIME POWER (PRP)

Available for an unlimited number of annual operating hours in variable-load applications, in accordance with ISO 8528-1.

TERMS OF USE

Nominal power is stated at 25 °C inlet-air temperature, 100 kPa barometric pressure (100 m A.S.L.) and 30% relative humidity.

RATED OUTPUT CURRENT BY VOLTAGE

Rated voltage	Standby current (550 kVA)	Prime current (500 kVA)
220/127 V	1443.4 A	1312.2 A
440/254 V	721.7 A	656.1 A
480/277 V	661.5 A	601.4 A

ENGINE DATA

Cummins KTA19-G3

GENERAL ENGINE DATA

Engine brand	Cummins
Engine model	KTA19-G3
Engine type	4-stroke diesel
Governor type	Electronic
Injection type	Direct
Aspiration type	Turbocharged and Aftercooled
Cylinders and arrangement	6-L

FUEL CONSUMPTION

100% load ESP	122 L/h
100% load PRP	111 L/h
75% load PRP	86 L/h
50% load PRP	61 L/h

AIR SYSTEM

Intake air flow	611 L/s
Cooling air flow	/

GENERAL ENGINE DATA

Bore × stroke	159 × 159 mm
Displacement	18.9 L
Cooling system	Water-cooled
Lube oil consumption at full load	0.5%-1% of fuel consumption
Compression ratio	13.9:1
Air filter	Dry

EXHAUST SYSTEM

Maximum exhaust temperature	491 °C
Exhaust gas flow	1579 L/s
Maximum allowed back pressure	10 kPa

STARTING SYSTEM

Starting power	9.0 kW
Recommended battery	120 Ah
Number of batteries	2
Auxiliary voltage	24 VDC

OIL AND COOLING CAPACITIES

Engine oil capacity	50 L
Total coolant capacity	30 (engine only) L

ALTERNATOR DATA

3-phase · Brushless · Electronic AVR

GENERAL ALTERNATOR DATA

Number of phases	3
Power factor (Cos Phi)	0.8
Poles	4
Winding connections (standard)	Star-series
Insulation	H class
Enclosure (according to IEC 34-5)	IP23
Excitation system	Self-excited, brushless
Voltage regulator	AVR (Electronic)
Number of bearings	Single bearing
Coupling system	Flexible disc
Coating type	Standard (vacuum impregnation)

CONTROL MODULE

Deep Sea DSE6120



SINGLE GEN-SET CONTROL

AMF CONTROL

Automatic mains failure controller for one gen-set, with three-phase mains and generator monitoring, flexible I/O and electronic or non-electronic engine versions.

CORE FUNCTIONS

01	Automatic transfer between mains and generator power	05	Event log for 10 events plus engine-hours counter
02	3-phase mains and generator voltage monitoring	06	6 digital inputs and 3 analog sender inputs
03	Generator current monitoring and protection	07	Six outputs; configuration depends on the engine version
04	CAN-engine or magnetic-pick-up/alternator-sensing versions	08	PC/front-panel configuration; optional IP65 front gasket

CONNECTIVITY

DSE6120 · Interfaces, sensing and I/O

USB CAN / MPU 6 INPUTS 6 OUTPUTS

COMMUNICATION AND MONITORING FEATURES

- | | | | |
|----|--|----|---|
| 01 | USB connects to DSE Configuration Suite for controller setup | 05 | Six digital inputs and three analog senders support field signals |
| 02 | Choose CAN-engine or magnetic-pick-up/alternator-sensing version | 06 | Four outputs are configurable on MPU/alternator version; six on CAN |
| 03 | DSE6120 includes dedicated 3-phase mains sensing | 07 | Remote-start input, test mode and configurable timers are included |
| 04 | 3-phase generator voltage and current monitoring is built in | | |

ORDERING OPTIONS

CAN ENGINE VERSION · MPU / ALTERNATOR VERSION

Engine sensing and output configuration depend on the selected controller variant.