

VW110-5

DIESEL GENERATOR SET / SILENT



110

kVA

STANDBY POWER

100

kVA

PRIME POWER

50

Hz

FREQUENCY

400/230

V

VOLTAGE

Weichai WP4.1D113E200

3 phase · 0.8 PF · 1500 rpm

CONFIGURATION COMPARISON

Configuration	Dimensions (L × W × H)	Dry weight	Fuel tank
Silent set	2720 × 1100 × 1650 mm	1520 kg	180 L

Performance, engine, alternator and controller data are common to both configurations.

GENERAL CHARACTERISTICS

VW110-5 · 50 Hz · 3 Phase

RATED PERFORMANCE

Standby Power (kVA)	110
Standby Power (kW)	88
Prime Power (kVA)	100
Prime Power (kW)	80
Power Factor (Cos Phi)	0.8
Diesel Engine	WP4.1D113E200
Frequency (Hz)	50
Rated Speed (rpm)	1500
Phase	3
Standard Voltage (V)	400/230
Available Voltages (V)	415/240 or 380/220

POWER DEFINITIONS

STANDBY POWER (ESP)

Available for supplying emergency power during a utility interruption. The stated rating follows ISO 8528-1.

PRIME POWER (PRP)

Available for an unlimited number of annual operating hours in variable-load applications, in accordance with ISO 8528-1.

TERMS OF USE

Nominal power is stated at 25 °C inlet-air temperature, 100 kPa barometric pressure (100 m A.S.L.) and 30% relative humidity.

RATED OUTPUT CURRENT BY VOLTAGE

Rated voltage	Standby current (110 kVA)	Prime current (100 kVA)
380/220 V	167.1 A	151.9 A
400/230 V	158.8 A	144.3 A
415/240 V	153.0 A	139.1 A

ENGINE DATA

Weichai WP4.1D113E200

GENERAL ENGINE DATA

Engine brand	Weichai
Engine model	WP4.1D113E200
Engine type	4-stroke diesel
Governor type	Electronic
Injection type	Direct
Aspiration type	Turbocharged
Cylinders and arrangement	4-L

FUEL CONSUMPTION

100% load ESP	24.4 L/h
100% load PRP	21.3 L/h
75% load PRP	16.0 L/h
50% load PRP	10.6 L/h

AIR SYSTEM

Intake air flow	96.6 L/s
Cooling air flow	/

GENERAL ENGINE DATA

Bore × stroke	105 × 118 mm
Displacement	4.1 L
Cooling system	Water-cooled
Lube oil consumption at full load	0.5%-1% of fuel consumption
Compression ratio	17.5:1
Air filter	Dry

EXHAUST SYSTEM

Maximum exhaust temperature	560 °C
Exhaust gas flow	101.5 L/s
Maximum allowed back pressure	10 kPa

STARTING SYSTEM

Starting power	4.5 kW
Recommended battery	60 Ah
Number of batteries	2
Auxiliary voltage	24 VDC

OIL AND COOLING CAPACITIES

Engine oil capacity	14 L
Total coolant capacity	9.4 (Engine only) L

ALTERNATOR DATA

3-phase · Brushless · Electronic AVR

GENERAL ALTERNATOR DATA

Number of phases	3
Power factor (Cos Phi)	0.8
Poles	4
Winding connections (standard)	Star-series
Insulation	H class
Enclosure (according to IEC 34-5)	IP23
Excitation system	Self-excited, brushless
Voltage regulator	AVR (Electronic)
Number of bearings	Single bearing
Coupling system	Flexible disc
Coating type	Standard (vacuum impregnation)

CONTROL MODULE

Deep Sea DSE6120

SINGLE GEN-SET CONTROL

AMF CONTROL

Automatic mains failure controller for one gen-set, with three-phase mains and generator monitoring, flexible I/O and electronic or non-electronic engine versions.



CORE FUNCTIONS

01	Automatic transfer between mains and generator power	05	Event log for 10 events plus engine-hours counter
02	3-phase mains and generator voltage monitoring	06	6 digital inputs and 3 analog sender inputs
03	Generator current monitoring and protection	07	Six outputs; configuration depends on the engine version
04	CAN-engine or magnetic-pick-up/alternator-sensing versions	08	PC/front-panel configuration; optional IP65 front gasket

CONNECTIVITY

DSE6120 · Interfaces, sensing and I/O

USB CAN / MPU 6 INPUTS 6 OUTPUTS

COMMUNICATION AND MONITORING FEATURES

- | | | | |
|----|--|----|---|
| 01 | USB connects to DSE Configuration Suite for controller setup | 05 | Six digital inputs and three analog senders support field signals |
| 02 | Choose CAN-engine or magnetic-pick-up/alternator-sensing version | 06 | Four outputs are configurable on MPU/alternator version; six on CAN |
| 03 | DSE6120 includes dedicated 3-phase mains sensing | 07 | Remote-start input, test mode and configurable timers are included |
| 04 | 3-phase generator voltage and current monitoring is built in | | |

ORDERING OPTIONS

CAN ENGINE VERSION · MPU / ALTERNATOR VERSION

Engine sensing and output configuration depend on the selected controller variant.